

IC-M304

Submersible compact body with large LCD and powerful audio





1m depth for 30 minutes

Compact and submersible Equivalent to IPX7 (1m depth for 30 minutes, except cables).

Large easy-to-see LCD Shows full size channel number with 4-step backlighting.

Built-in DSC

For distress calls, or for position request/position report.

New Force5Audio™ speaker

Delivers impressive audio output with powerful bass.

Favorite channel function

Offers quick channel selection from the microphone up/down buttons.

AquaQuake draining function

The vibrating "buzz" sound clears water away from the speaker grill.

Weather channel with weather alert Listen for important weather broadcasts.

Dualwatch and Tri-watch functions

Monitors Ch.16 and/or call channel, while using another channel

SPECIFICATIONS

GENERAL

Frequency range : Tx 156.025–157.425MHz

Rx 156.050-163.275MHz

: USA, CAN, INT, WX Usable channels

channels

 Type of emission : 16K0G3E, 16K0G2B · Power supply : 13.8V DC ±15%

· Current drain : Tx 5.5A (at 25W output) (at 13.8V DC) Rx 1.5A (at AF max.)

· Operating temperature range:

-20°C to +60°C; -4°F to +140°F

Antenna impedance: 50Ω (SO-239)

• Dimensions (W×H×D, projections not included):

 $153 \times 67 \times 133$ mm; $6\frac{1}{32} \times 2\frac{5}{8} \times 5\frac{1}{4}$ in.

• Weight (approx.) : 825g; 1.8lb

: NMEA version 2.0 or 3.01 NMEA formats

RMC, GGA, GNS, GLL

Measurements made in accordance with TIA/EIA 603. All stated specifications are subject to change without notice or obligation.

TRANSMITTER

 Output power : 25W or 1W (at 13.8V DC)

· Modulation system: Variable reactance frequency modulation

 Max. freq. deviation: ±5kHz • Frequency error : ±10ppm

• Spurious emissions: Less than -70dBc (at 25W)

· Adj. channel power: More than 70dB

· Audio harmonic distortion

: Less than 10% (at 60% dev.)

· Residual modulation: More than 40dB

RECEIVER

· Intermediate freq.: 1st 21.7MHz, 2nd 450kHz

: 0.22µV typical at 12dB SINAD

Squelch sensitivity: Less than 0.22uV

· Adj. Ch. selectivity: More than 70dB

· Spurious response: More than 70dB

 Intermodulation : More than 70dB

· Hum and noise · More than 40dB

· Audio output power: 4.5W typical at 10% distortion

with a 4Ω load

DIMENSIONS 137.0 (5 ¹³/₃₂) $(5^{21/32})$ (5.1/4)133 153.0 (6 1/32) **©**[42.2 86.3 (3 13/3e) (1 ²¹/₃₂) Unit: mm (inch)

Color versions:

Black

Super white

Supplied accessories:

· DC power cable

 Hand microphone · Mounting bracket kit

FORCE5AUDIO logo is a registered trademark of Icom Inc. (Japan) in the United States.

OPTIONS

• HM-164B/164SW/164G HAND MICROPHONE Black, super white and gray are available. Same as supplied.

• MR-69

FLUSH MOUNT KIT For flush-mounting the IC-M304 to a flat surface such as an instrument control panel.




MB-92 DUST COVER

Protects the IC-M304 from dust and strong sunlight when the radio is not in use



REAR PANEL CONNECTIONS



- 1 External speaker lead; (+): Blue, (-): Gray
- 2 GPS receiver lead (NMEA IN);

(+): Yellow, (-): Green

- 3 DC power connector; (+): Red, (-): Black
- 4 Antenna connector

ICOM Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: http://www.icom.co.jp/world/index.html

Count on us!

Icom America Inc.

2380 116th Avenue NE, Bellevue, WA 98004, U.S.A. Phone: +1 (425) 454-8155 Fax: +1 (425) 454-1509 E-mail: sales@icomamerica.com
URL: http://www.icomamerica.com

Icom Canada

Glenwood Centre #150-6165 Highway 17. Delta, B.C., V4K 5B8, Canada Phone: +1 (604) 952-4266 Fax: +1 (604) 952-0090 E-mail: info@icomcanada.com URL: http://www.icomcanada.com

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road, Clayton VIC 3168 Australia Phone: +61 (03) 9549 7500 Fax :+61 (03) 9549 7505 E-mail: sales@icom.net.au URL: http://www.icom.net.au

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand Phone: +64 (09) 274 4062 Fax : +64 (09) 274 4708 E-mail : inquiries@icom.co.nz URL : http://www.icom.co.nz

Icom (Europe) GmbH

Communication Equipment Himmelgeister Str. 100, D-40225 Düsseldorf, Germa Phone: +49 (0211) 346047 : +49 (0211) 333639 E-mail : info@icomeurope.com : http://www.icomeurope.com

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer 08190, Sant Cugat del Valles, Barcelona, Spain Phone: +34 (93) 590 26 70

Fax : +34 (93) 589 04 46 E-mail : icom@icomspain.com URL: http://www.icomspain.com

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K. Phone: +44 (01227) 741741 Fax: +44 (01227) 741742 E-mail: info@icomuk.co.uk URL: http://www.icomuk.co.uk

Icom France s.a.s.

Zac de la Plaine. 2ac de la Plaine, 1 Rue Brindejonc des Moulinais, BP 45804, 31505 Toulouse Cedex 5, France Phone : +33 (5) 61 36 03 03 Fax : +33 (5) 61 36 03 00 E-mail: icom@icom-france.com : http://www.icom-france.com

Icom Polska

Sopot, 3 maja 54, Poland

Phone: +48 (58) 550 7135
Fax :+48 (58) 551 0484
E-mail: icompolska@icompolska.com.pl
URL : http://www.icompolska.com.pl

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C. Phone: +886 (02) 2559 1899 Fax: +886 (02) 2559 1874 E-mail: sales@asia-icom.com

LIRI · http://www.asia-icom.com

Your local distributor/dealer: